



MODEL OVERVIEW

MANUFACTURER	HYUNDAI
MODEL	HY10000LEK
TYPE	PORTABLE
MAX POWER	8000W
RATED POWER	7250W

HY10000LEK GENERATOR

The **Hyundai HY10000LEK** is a compact, high-capacity generator delivering **8000W (10kVA)** stable power with an auto voltage regulator (AVR) alternator. It is ideal for domestic standby or residential / commercial emergency power.

Whether you are welding or fixing fences on your farm, powering tools on the job site or need back up power for your house or shed, the HY10000LEK provides a cost-effective, fuel-efficient solution without compromising on performance.

TECHNICAL

ENGINE MODEL	HY457
STARTING	ELECTRIC and RECOIL
FUEL TYPE	PETROL
FUEL TANK CAPACITY	25L
RUN TIME	7.5 HRS @ 50% LOAD
PHASE / VOLTAGE	SINGLE PHASE / 240V
WARRANTY	12 MONTHS or 100 HRS LIMITED*

NOISE

NOISE RATING	73 dB @ 7 M
--------------	-------------

OUTLETS

OUTLETS & SOCKETS	1 x 15 AMP 240V 1 X 32 AMP 240V
-------------------	------------------------------------

DIMENSIONS

LENGTH	700 MM
WIDTH	550 MM
HEIGHT	560 MM
WEIGHT	91.2 KG

*12 months or 100 hours (whichever comes first) Limited Warranty: This warranty covers defects in materials and workmanship under normal use and maintenance for a period of 12 months or 100 hours (whichever comes first) from the date of purchase. It applies only to the original purchaser and is non-transferable.

The warranty does not cover damage caused by misuse, neglect, accident, improper installation, unauthorised repairs or modifications, normal wear and tear, or use of non-approved fuels or oils. Consumable parts such as filters, fuses, and cosmetic wear are not covered.

The generator must be serviced at regular intervals as specified in the user manual. Proof of purchase and service records may be required. As the Australian distributor, Genelite reserves the right to repair or replace defective parts at its discretion.

